### High Performance Bus Interface Solutions

## 16AO4MFS

## Four-Channel 16-Bit High-Speed Analog Output PMC Board

With 400,000 Samples per Second per Channel, and Independent Clocking

Available in PMC, PCI, cPCI and PC104-Plus and PCI Express form factors as:

PMC-16AO4MFS: PMC, Single-width PCI-16AO4MFS: PCI, short length

cPCI-16AO4MFS: cPCI, 3U
PC104P-16AO4MFS: PC104-Plus
PCIe-16AO4MFS: PCI Express

PCle104-16AO4MFS: PCle, one-lane on PC/104 form factor

See Ordering Information for details.

Call for availability of other form factors, such as XMC, CCPMC, etc.

#### Features:

- Four Precision 3-Wire Balanced Differential High-Speed Analog Output Channels;
- 16-Bit Resolution; D/A Converter per Channel
- Data Rates to 400 K-Samples per Second per Channel; 1600 KSPS Aggregate Rate
- Output Ranges of  $\pm 12V$ ,  $\pm 10V$  or  $\pm 5V$
- Four Independent 32 K-Sample Analog Output FIFO Buffers
- Output Data Buffer Size Adjustable from Four Samples to up to 32 K-Samples
- High Stability Timebase; 20PPM
- Continuous and Burst Clocking Modes
- Seamless Waveform Sequencing
- Data Rates Controlled by Independent Internal Clocks, or by an External Clock
- Supports Multiboard Synchronization;
- Software-Selectable TTL or Differential External Clock I/O
- Internal Autocalibration of All Channels
- High Accuracy; 0.023% FSR max error on  $\pm 10$ V Range, INL = 0.007%
- Fast Settling; 5 us to 0.1%; 8 us to 0.01%; with No-filter Option
- Bidirectional Byte-Wide Digital Port

### Applications:

✓ Precision Voltage Source ✓ Acoustic Research ✓ Waveform Synthesis

✓ Industrial Robotics ✓ Audio Synthesis ✓ Arbitrary Functions

**REV: 080510** 

#### **High Performance Bus Interface Solutions**

#### Functional Description:

The PMC-16AO4MFS board provides four independent 3-wire balanced differential 16-bit D/A converter channels, and all supporting functions necessary for adding precision high-speed analog output capability to a PMC host. The board is functionally compatible with the IEEE PCI local bus specification Revision 2.2, and supports the "plug-n-play" initialization concept. Unique FIFO buffer controls support the seamless sequencing of successive waveforms. In less demanding applications, the outputs can be updated individually. Both TTL and differential I/O ports support multiboard synchronization.

A PCI interface adapter provides the interface between the controlling PCI bus and the internal local controller (Figure 1). Four analog output channels are controlled through independent analog output FIFO buffers, and can be updated either simultaneously or sequentially. The clocking rate for each output channel can be controlled either by a dedicated internal rate generator, or by an external clock. The local controller manages all local configuration and data manipulation functions, including autocalibration. Analog output levels are initialized to zero (midrange).

Internal autocalibration networks permit calibration to be performed without removing the board or host from the system. This feature produces the optimum calibration situation, in which the board is calibrated in its actual operating environment,




Figure 1. PMC-16AO4MFS Board; Functional Organization

The board is designed for minimum off-line maintenance, and includes internal monitoring features that eliminate the need for disconnecting or removing the module from the system for calibration. All input and output system connections are made through a single I/O connector. Power requirements consist of +5 VDC in compliance with the PCI specification, and operation over the specified temperature range is achieved with conventional convection cooling.

## **High Performance Bus Interface Solutions**

#### **ELECTRICAL SPECIFICATIONS**

At +25 °C, with specified operating voltages

#### **Output Characteristics:**

Configuration: Four balanced differential 3-wire (true/complement) analog output channels,

with a dedicated 16-Bit DAC per channel

Voltage Ranges: Factory configured as  $\pm 12$  Volts,  $\pm 10$  Volts or  $\pm 5$  Volts

Output Resistance: Output: 1.0 Ohm maximum

Output protection: Withstands sustained short-circuiting to ground without damage

Load Current: Zero to  $\pm 5$  milliamps

Load Capacitance: Stable with zero to 2000 pF shunt capacitance

Settling Time: No Filter: 5 us to 0.1%, 8 us to 0.01%

10 kHz Filter: 130 us to 0.1%, 160 us to 0.01%

Noise: No Filter: 4 mVRMS, 10 Hz - 100 KHz

10 kHz Filter: 2 mVRMS, 10 Hz - 100 KHz

Glitch Impulse: ±5V Range: 5 nV-Sec

 $\pm 10V$ ,  $\pm 12V$  Ranges: 8 nV-Sec

#### **Transfer Characteristics:**

Resolution: 16 Bits (0.0015 percent of FSR)

Sample Clocking Rate: Master Rate Clock: 460 to 400,000 samples per second per channel

Adjustable-Rate Clock: 460 to 375,000 samples per second per channel External Rate Clock: Zero to 375,000 samples per second per channel.

DC Accuracy: Range Midscale Accuracy ±Fullscale Accuracy

(Max error, no-load)  $\pm 12V$   $\pm 2.5mv$   $\pm 5.2mv$ 

 $\pm 10 \text{V}$   $\pm 2.0 \text{mv}$   $\pm 4.6 \text{mv}$   $\pm 5 \text{V}$   $\pm 1.5 \text{mv}$   $\pm 2.9 \text{mv}$ 

Bandwidth, -3dB: No output filter option: 300 kHz typical

10 kHz filter option: 10 kHz typical (Single-pole lowpass)

Crosstalk Rejection: 80 dB, DC-10 kHz

Common Mode Offset:  $\pm 10$ mV from output return.

Integral Nonlinearity:  $\pm 0.007$  percent of FSR, maximum

Differential Nonlinearity:  $\pm 0.003$  percent of FSR, maximum

# General Standards Corporation High Performance Bus Interface Solutions

#### **☐** Operating Modes and Controls

Sample Clock Source: Internal rate generators, external hardware clock input, or software clock. The

external clock output can be used for synchronization of multiple

PMC-16AO4MFS boards.

Each output channel can be clocked from an independent internal rate generator, or all channels can be clocked synchronously. Rate generator frequencies\* are independently adjustable from 16MHz to 32MHz with 0.2 percent resolution and 0.02 percent accuracy, and are derived from the local crystal-controlled master clock. Rate generator outputs are divided by independent 16-bit counters to provide the output channel clocks.

External sync I/O is software-selectable as either TTL-compatible, or as 2-wire LVDS differential pairs. The Sync I/O signals can be operated either as output clocks, or as burst triggers.

\* In addition to the basic adjustable rate generator frequencies, up to eight custom fixed clocking frequencies can be specified from 500SPS to 375KSPS as a factory option. Clock stability is 20PPM.

Software control bit, or external sync input. Burst Trigger:

Clocking Modes: Continuous or burst

Active Buffer Size: From 4 output values to 32K-values in 2:1 steps; each buffer.

Buffer Modes: Circular (closed) for periodic waveforms, or Open for continuous functions

Data Format: Software selected as offset binary or as Two's complement

#### AUTOCALIBRATION

During autocalibration, each analog channel is calibrated to a single precision internal voltage reference that is adjustable with a single trimmer. Auto calibration can be invoked at any time after initialization.

#### PCI INTERFACE

#### **Analog Output Buffers**

Analog output data is written to the board through four registers that serve as FIFO buffer ports. Each buffer is 17 bits wide, has a software-controlled capacity of from four output values to 32K values, and is right justified to the LSB in the D32 PCI data path. Output data is a 16-bit field that is softwareconfigurable in either Two's complement or offset binary format. The 17th bit is used as an end-of-frame (EOF) flag for tracking functions through the buffer.

**PCI Compatibility:** Conforms to PCI Specification 2.3, with 33MHz, 5V/3.3V, D32 transactions.

Supports "plug-n-play" initialization.

Single multifunction interrupt.

Supports block-mode DMA transfers to the output buffers as bus master.

### General Standards Corporation

## **High Performance Bus Interface Solutions**

#### MECHANICAL AND ENVIRONMENTAL SPECIFICATIONS

#### **Power Requirements**

+5VDC ±0.2 VDC at 1.4 Amps maximum, 1.0 Amp typical. Outputs fully loaded.

Maximum Power Dissipation: Side-1: 5.5 Watts maximum, 4.0 Watts typical

Side-2: 1.4 Watt maximum, 1.0 Watt typical.

#### **Physical Characteristics (PMC Form Factor)**

Height: 13.5 mm (0.53 in)

Depth: 147.5 mm (5.807 in); 1.5mm less than standard PMC,

Width: 74.0 mm (2.91 in)

#### **Environmental Specifications**

Ambient Temperature Range:

Operating:

Commercial: 0 to +65 degrees Celsius inlet air Ruggedized: \* 0 to +80 degrees Celsius inlet air

\* Industrial-temp components; conformally coated.

Storage: -40 to +85 degrees Celsius

Relative Humidity: Operating: 0 to 80%, non-condensing; (90% ruggedized).

Storage: 0 to 95%, non-condensing

Altitude: Operation to 10,000 ft.

Cooling: Conventional convection cooling.

# General Standards Corporation High Performance Bus Interface Solutions

#### ORDERING INFORMATION

Specify the basic product model number (PMC-16AO4MFS), followed by an option suffix "A-B-C-D" as indicated in the table below. For example, model number PMC-16AO4MFSIC-12V-NF describes a ruggedized board with a  $\pm 12$  Volt output range, no output filters, and standard clocking frequencies.

Basic Model Number	Form Factor	
PMC-16AO4MFS	PMC (Native)	
PCI-16AO4MFS <sup>1</sup>	PCI, short length	
cPCI-16AO4MFS <sup>1</sup>	cPCI, 3U	
PCIe-16AO4MFS <sup>1</sup>	cPCI, 3U	
PC104P-16AO4MFS	PC104-Plus	
PCle104-16AO4MFS 1,2	PCIe, one-lane on PC/104 form factor	

<sup>&</sup>lt;sup>1</sup> Module installed and tested on an adapter, with mechanical and functional equivalency. Contact factory for availability in native form factors.

<sup>&</sup>lt;sup>2</sup> PCIe104 supports only the PCIe bus.

Optional Parameter	Value	Specify Option As:
Operating Environment	Commercial Grade	A = (Blank)
	Ruggedized	A = IC
Output Range:	±5 Volts	B = 5V
	±10 Volts	B = 10V
	±12 Volts	B = 12V
Output Lowpass Filter:	No output Filter	C = NF
	10 kHz Output Filter	C = F
Custom Clocking Frequencies:	No custom frequencies	D = NCF
(8 Maximum)	Custom frequencies *	D = (1-8)CF
	Standard frequencies: 224.0000 kHz ±0.01% 60.0000 kHz ±0.01% 27.3040 kHz ±0.01% 22.5000 kHz ±0.01%	D = (Blank)

<sup>\*</sup> Specify required frequencies and accuracies ( $\pm 0.01$  percent). Contact factory for availability.

# General Standards Corporation High Performance Bus Interface Solutions

#### SYSTEM I/O CONNECTIONS

**Table 1. System Connector Pin Functions** 

	ROW-A
PIN	SIGNAL
1	ANA OUTPUT 00 LO
2	ANA OUTPUT 00 HI
3	OUTPUT RETURN
4	OUTPUT RETURN
5	ANA OUTPUT 01 LO
6	ANA OUTPUT 01 HI
7	OUTPUT RETURN
8	OUTPUT RETURN
9	VRANGE RETURN
10	VRANGE OUTPUT
11	VRANGE RETURN
12	OUTPUT RETURN
13	ANA OUTPUT 02 LO
14	ANA OUTPUT 02 HI
15	OUTPUT RETURN
16	OUTPUT RETURN
17	ANA OUTPUT 03 LO
18	ANA OUTPUT 03 HI
19	OUTPUT RETURN
20	OUTPUT RETURN
21	DIGITAL RTN
22	TTL SYNC INP L
23	DIGITAL RTN
24	TTL CLK INP L
25	DIGITAL RTN
26	DIGITAL RTN
27	DIFF SYNC INP LO
28	DIFF SYNC INP HI
29	DIGITAL RTN
30	DIGITAL RTN
31	DIFF CLK INP LO
32	DIFF CLK INP HI
33	DIGITAL RTN
34	DIGITAL RTN

ROW-B		
PIN	SIGNAL	
1	DIGITAL RTN	
2	DIGIO 00	
3	DIGITAL RTN	
4	DIGIO 01	
5	DIGITAL RTN	
6	DIGIO 02	
7	DIGITAL RTN	
8	DIGIO 03	
9	DIGITAL RTN	
10	DIGIO 04	
11	DIGITAL RTN	
12	DIGIO 05	
13	DIGITAL RTN	
14	DIGIO 06	
15	DIGITAL RTN	
16	DIGIO 07	
17	DIGITAL RTN	
18	DIGITAL RTN	
19	DIGITAL RTN	
20	DIGITAL RTN	
21	DIGITAL RTN	
22	TTL SYNC OUT L	
23	DIGITAL RTN	
24	TTL CLK OUT L	
25	DIGITAL RTN	
26	DIGITAL RTN	
27	DIFF SYNC OUT LO	
28	DIFF SYNC OUT HI	
29	DIGITAL RTN	
30	DIGITAL RTN	
31	DIFF CLK OUT LO	
32	DIFF CLK OUT HI	
33	DIGITAL RTN	
34	DIGITAL RTN	




Figure 2. System Input/Output Connector

#### **System Mating Connector:**

68-Pin 2-row 0.050" dual-ribbon cable socket connector: with a metal shell Robinson-Nugent #P50-068-DDSTG.

Contact factory for availability of the 68-pin AMP SCSI-3 connector.

General Standards Corporation assumes no responsibility for the use of any circuits in this product. No circuit patent licenses are implied. Information included herein supersedes previously published specifications on this product and is subject to change without notice.

## **General Standards Corporation**